



uBox LTE modem B310s-22

Wi-Fi connectivity (STA management)	possibility to connect with Wi-Fi up to 32 devices (802.11b/g/n)
interfaces and indicators	<p>One power adapter port One WAN/LAN port (RJ45) One phone port (RJ11) Two external LTE antenna ports (SMA-J1.5) One SIM card slot Built-in LTE/UMTS/GSM primary antenna Built-in LTE/UMTS secondary antenna Built-in WLAN 2.4G antenna One power indicator One Internet status indicator One Wi-Fi/WPS indicator One LAN indicator One group of signal strength indicators One Power ON or OFF switch One WPS button One Reset button</p>
frequency	<p>LTE: Band 1/3/7/8/20/38 FDD 2100 MHz/1800 MHz/2600 MHz/900 MHz/800 MHz TDD 2600 MHz UMTS: Band 1/8 2100 MHz/900 MHz GSM: Band 2/3/5/8 1900 MHz/1800 MHz/850 MHz/900 MHz WLAN 2.400 GHz - 2.4835 GHz</p>
transmission (max. data rate)	<p>LTE FDD: DL 150 Mbps, UL 50 Mbps LTE TDD: DL 112 Mbps, UL 10 Mbps DC-HSPA+: DL 42 Mbps, UL 5.76 Mbps HSPA+: DL 21 Mbps (64QAM) / 28 Mbps (MIMO), UL 5.76 Mbps HSPA: DL 14.4 Mbps, UL 5.76 Mbps WCDMA PS: 384 kbps EDGE: DL 296 kbps, UL 236.8 kbps GPRS: 85.6 kbps</p>
dimensions	<p>181 mm × 126 mm × 36 mm (length × width × height)</p>

weight	About 226 g (excluding the power supply adapter)
working environment	Working temperature: 0°C to 40°C Storage temperature: -20°C to +70°C working humidity: 5% - 95%
system required	Windows 8.1, Windows 8, Windows 7, Windows Vista SP1/SP2, Windows XP SP3, and Mac OS X 10.9, 10.8, and 10.7 with latest upgrades

price	
Subscription to uGo 12500 with 12 or 24 months' commitment	1 AMD
Without commitment	50 000 AMD

After expiry of commitment period the device becomes subscriber's property.

The SIM-card designed for uBox service can only be used with the uBox equipment of Ucom. Please, do not remove or damage the safety valve on the equipment without the company's consent. Otherwise, it will be considered as a breach of the Subscription Agreement.