



uBox LTE modem B310s-22

Wi-Fi connectivity (STA management)	possibility to connect with Wi-Fi up to 32 devices (802.11b/g/n)
interfaces and indicators	One power adapter port One WAN/LAN port (RJ45) One phone port (RJ11) Two external LTE antenna ports (SMA-J1.5) One SIM card slot Built-in LTE/UMTS/GSM primary antenna Built-in LTE/UMTS secondary antenna Built-in WLAN 2.4G antenna One power indicator One Internet status indicator One Wi-Fi/WPS indicator One LAN indicator One group of signal strength indicators One Power ON or OFF switch One WPS button One Reset button
frequency	LTE: Band 1/3/7/8/20/38 FDD 2100 MHz/1800 MHz/2600 MHz/900 MHz/800 MHz TDD 2600 MHz UMTS: Band 1/8 2100 MHz/900 MHz GSM: Band 2/3/5/8 1900 MHz/1800 MHz/850 MHz/900 MHz WLAN 2.400 GHz - 2.4835 GHz
transmission (max. data rate)	LTE FDD: DL 150 Mbps, UL 50 Mbps LTE TDD: DL 112 Mbps, UL 10 Mbps DC-HSPA+: DL 42 Mbps, UL 5.76 Mbps HSPA+: DL 21 Mbps (64QAM) / 28 Mbps (MIMO), UL 5.76 Mbps HSPA: DL 14.4 Mbps, UL 5.76 Mbps WCDMA PS: 384 kbps EDGE: DL 296 kbps, UL 236.8 kbps GPRS: 85.6 kbps
dimensions	181 mm × 126 mm × 36 mm (length × width × height)

weight	About 226 g (excluding the power supply adapter)
working environment	Working temperature: 0°C to 40°C Storage temperature: -20°C to +70°C working humidity: 5% - 95%
system required	Windows 8.1, Windows 8, Windows 7, Windows Vista SP1/SP2, Windows XP SP3, and Mac OS X 10.9, 10.8, and 10.7 with latest upgrades

price	
Subscription to uGo 12500 with 12 or 24 months' commitment	1 AMD
Without commitment	50 000 AMD

По истечении срока подписки устройство становится собственностью абонента.

SIM-карта, предназначенная для того, чтобы воспользоваться услугой **uBox** может быть использована исключительно с устройством **uBox** от **Ucom**. Просим не удалять и не повреждать предохранительный клапан на устройстве без согласия компании. В противном случае это будет расценено, как нарушение абонентского договора.